

POTENTIOSTAT/GALVANOSTAT WITH WAVEFORM GENERATOR

N600-HAB151

APPLICATIONS

- Current Testing
- Coulometry
- Corrosion
- Physical Electrochemistry
- Voltammetry
- Polarization



Model N600-HAB151 is designed to provide a complete potentiostat/galvanostat/function generator instrument for electrochemical research. It offers a high quality portable system capable of voltammetry, coulometry, automatic polarization and other studies. This unit incorporates features from both the **N600-HA151B Potentiostat** and the **N600-HB111A Function Generator**. The potentiostat/galvanostat portion with a maximum output of $\pm 15V/\pm 1A$ and six current ranges (the lowest range: $\pm 10\mu A$) is adequate for most electrolysis tests and corrosion studies.

Also included in this portion are an external control input, a current detecting filter, and warning lamps for "OUT-OF-CONTROL", "POTENTIAL-OVER", and "CURRENT-OVER". The function generator portion utilizes analog circuitry to yield smooth slopes. It also offers a wide scanning speed range (0.1mV/sec.~5000V/min) and a potential setting range of -5.0V to +5.0V. The STOP, HOLD, and REVERSE buttons are also included. This model consists of a potentiostat, a galvanostat, an electrometer, and a function generator. The function generator portion is connected to the rest of the unit via the ON/OFF switch.

As a Potentiostat

- | | |
|-------------------------------|--|
| (a) Maximum Output | $\pm 15V, \pm 1A$ |
| (b) Current Measuring Range | $\pm 1A, \pm 100mA, \pm 10mA, \pm 1mA, \pm 100\mu A, \pm 10\mu A$ (6 ranges) |
| (c) Maximum Control Potential | $\pm 10V$ |
| (d) Control Accuracy | $< \pm 3mV$ |
| (e) Response Time | $< 50\mu sec$ |
| (f) Reference Input Impedence | $> 10^{10} \Omega$ |

As a Galvanostat

- | | |
|------------------------------|--|
| (a) Maximum Output | (6 ranges) $\pm 1A, \pm 100mA, \pm 10mA, \pm 1mA, \pm 100\mu A, \pm 10\mu A$ |
| (b) Current Setting Range | $\pm 10V$ |
| (c) Current Setting Accuracy | $< \pm 1\%$ of range full scale |
| (d) Response time | $< 50\mu sec$ |

As an Electrometer

- | | |
|-----------------------------|---|
| (a) Input Resistance | $> 10^{10} \Omega$ |
| (b) Bias Current | $< 10^{-10} A$ |
| (c) Response Time | $< 10\mu sec$ |
| (d) Conversion Accuracy | $< \pm 0.1\%$ of input potential |
| (e) Potential Display Range | $\pm 2V$ and $\pm 10V$ full scale (Digital Display) |

As a Function Generator

- | | |
|------------------------|---|
| (a) Waveforms | Ramp
One-shot triangle
One-shot double triangle
Repetitive triangle |
| (b) Setting Potentials | Range: $-5,000V \sim +5,000V$
Setting: Initial, upper, and lower potentials can be set independently (INITIAL, HIGH, LOW) |
| (c) Scanning Speed | Setting 1: $1 \times 10^{-1}, 1 \times 10^2, 1 \times 10^3, 1 \times 10^4$
Setting 2: 1, 2, 5
Setting Units: mV/sec, 100mV/min
Setting Accuracy: $< \pm 1\%$ (for $x1 \sim x10$); $< \pm 2\%$ (for $x10^{-1}$) |
| (d) Switches | START/STOP
HOLD (output potential drift $< \pm 0.001mV/sec$)
REVERSE |

Recording Output

- | | |
|--------------------------------|--------------------------------------|
| (a) Potential Recording Output | Input/output conversion ratio is 1:1 |
| (b) Current Recording Output | 1V output for every range full scale |

For a complete listing of our Science Education instruments, please browse our online catalog at

www.nadascientific.com